

Deter 200 (Model 2705)

Portable battery-powered fence charger



A low-cost fence control alternative

Hallman's Deter 200 is a lightweight, portable fencer that can power up to 2 miles of fence wire. The Deter 200 provides more than 4 weeks of continuous use (24 hours a day, 7 days a week) on 4 D-cell alkaline batteries

The Deter 200 was designed for primarily for portable corrals, making them easier to erect and eliminating rope burn on horses while camping on trail rides. The Deter 200 is also ideal for a variety of other permanent and temporary uses, including:

- ◆ Temporary strip grazing
- ◆ Crop protection
- ◆ Protecting vegetable gardens from dogs and other 'pests'
- ◆ Protecting hay storage or farm yards
- ◆ Protecting supplies from foraging nocturnal animals on camping or hiking trips

Features

- ◆ Safe, effective, and easy to install
- ◆ Direct-current pulse, low impedance, battery-powered operation
- ◆ Capable of powering up to 2 miles of fence wire
- ◆ Exceptional battery life—up to four weeks on four D-cell alkaline batteries (not included)
- ◆ UV-resistant, water-resistant, and fire-resistant enclosure
- ◆ Lightweight—weighs less than three pounds with the batteries installed
- ◆ One-year limited warranty (includes lightning damage)

Ratings

Model	Type	No load voltage	Guard voltage								
			½ mi. 0.8 km	1 mi.* 1.6 km	2 mi. 3.2 km	3 mi. 4.8 km	5 mi. 8 km	10 mi. 16 km	30 mi. 48 km	50 mi. 80 km	
Shur Shock	AC	2,400	6,300	6,100	5,800	5,600	4,700	3,800	1,800	1,200	
Stockman	AC	4,500	11,500	10,300	8,300	6,800	5,700	4,000	2,100	1,500	
Battery Saver	DC	High	4,500	9,100	9,300	7,400	6,700	5,400	3,800	1,800	1,200
		Low	4,200	5,200	5,100	4,450	3,800	3,500	2,100	1,000	—
Trident	AC	High	6,000	9,300	9,000	8,900	8,700	8,700	7,600	5,200	4,500
		Med	3,000	4,300	4,800	5,000	5,000	4,500	3,700	3,500	3,000
		Low	1,200	2,000	2,000	2,000	2,000	2,000	2,000	2,000	—
Deter 200	DC	5,200	4,360	2,920	2,200	1,680	1,220	840	—	—	
Solar 6	Solar/DC	5,200	4,360	2,920	2,200	1,680	1,220	840	—	—	

* 100,000 Ω, 0.015 μF The above ratings are based on well-insulated, single-wire fence.
The lowest effective guard voltage for long-haired animals is 2,000 volts.
The lowest effective guard voltage for short-haired animals is 700 volts.

Additional information

For more information about the Deter 200 or other Hallman products and accessories, contact your dealer or visit www.hallman.ca.